

GWU627W6

Universal Wi-Fi N Adapter Multi-Language Version



The new IOGEAR Universal Wi-Fi N Adapter allows you to connect your device such as a Blu-ray player, HDTV, or game console to any wireless-N network in your home or office. The wireless-N (IEEE™ 802.11n) Adapter works with any device with an Ethernet port. No need to purchase an USB adapter that only works with a specific brand or device. After configuring the GWU627, simply connect the adapter to your device without worrying about re-wiring your home.

Using dual antennas (1T1R) this product provides data rates up to 150Mbps and reduces Wi-Fi dead zones in your wireless environment. This new standard supplies sufficient bandwidth for faster file transfer, music downloads, video streaming, on-line gaming & HD multi-media applications. In addition to the increased speed and coverage, you will be pleased to know that it is compatible with your existing 802.11b and 802.11g routers and access points. The unit also features a WPS (Wi-Fi Protected SetupTM) button offering a quick and secure network setup.

Avoid long stringing cables and enjoy the freedom to place your home entertainment center anywhere and still be connected to the Internet.

- Add high-speed 802.11n Internet access to any ethernet enabled device such as a Blu-ray player, DVR, HDTV, game console or media
- Wi-Fi N technology improves effective throughput and range over existing 802.11b/g products
- Compatible network standards: IEEE 802.11n (up to 150Mbps) IEEE 802.11g (up to 54Mbps) IEEE 802.11b (up to 11Mbps)
- Push-button Wi-Fi Protected Setup™ (WPS) simplifies secure and easy wireless configuration
- WEP, TKIP, AES, WPA and WPS2 hardware encryption schemes
- Convenient LED status indicators
- Plug and Play No special drivers required
- Compact and stylish design
- Avoid long stringing cable and enjoy the freedom to place your home entertainment center anywhere and still connect to the Internet
- Option to power by USB port means no exposed wire hanging from the TV









Connect device to Ethernet enabled device via RJ-45 cable Power the device via an available USB Port or attach to the power adapter Wirelessly connect your HDTV, game console, Blu-rayTM and more to your Router' "Wireless router not included

Requirements

Package Contents

- Operating System
 - Windows® XP
 , Windows®
 Vista,
 Windows® 7,
 Windows 8.x
 - Mac OS X v10.4 and above
 - Linux® Fedora 10 (Kernel: 2.6.27.5-117)
- Wireless network with WPS setup
- Wireless network without WPS setup and computer

- 1 x Universal Wi-Fi Adapter
- 1 x USB Power Cable
- 1 x Power Adapter (US, EU, and UK Prongs)
- 1 x Ethernet Cable
- 3 x Quick Start Guide (English, Spanish, French)
- 1 x Warranty / Registration Card



Specifications

Function	GWU627W6	Dimensions	GWU627W6
Power Consumption	Transmit: < 380mA.; Receive: < 250mA.	POP Information	
Operating Temperature	0 ~ 50 celsius	10" Peg Hook	4
Storage Temperature	-10 ~ 70 celsius	6" Peg Hook	3
USB Specification	USB 2.0	Unit Dimensions	
Humidity	5 ~ 90% (non-condensing)	Width	2 7/8"
Transmission Power	17 dBm	Height	5/8"
Frequency Band	2.4GHz ~ 2.483GHz unlicensed ISM band	Depth	2"
Modulation	IEEE 802.11n: BPSK, QPSK, 16-QAM, 64-QAM	Inner Pack	
Data Rate	IEEE 802.11n : 6, 9, 12, 18, 24, 36, 48, 54, 60, 90, 120 and up to 150Mbps	Width	14"
		Height	7.5"
Interface	USB 2.0	Depth	9.5"
Security	64-bit or 128-bit WEP/WPA TKIP	Inner Pack Qty.	6
Management	Windows-based Utility	Unit Package Dimensions	
Operating Range	100 - 400m, depending on surrounding environment	Width	6.25"
Encryption	64 bit / 128 bit WEP, TKIP, AES	Height	7.5"
Antenna Type	On board chip antenna	Depth	2.25"
Range	Up to 320 ft	Master Carton	
		Width	15"
		Height	15"
		Depth	10.5"
		Master Carton Qty.	12
		Weight	
		Master Carton Wt.	10.72 lb
		Inner Pack Wt.	4.56 lb
		Unit Pack Wt.	0.62lb
		Unit Wt.	0.08lbs